

## Flat cable terminal, 3p, size 4

Part no. **NZM4-XKB**  
 Catalog No. **266829**

Similar to illustration

## Delivery program

Accessories			Terminals
Rated current	$I_n$	A	$\leq 1100$
For use with			NZM4, N(S)4
<b>Terminal capacities</b>			
Cu strip (number of segments x width x segment thickness)		mm <sup>2</sup>	min. 6 x 16 x 0.8 max. (2 x) 10 x 32 x 1.0
<b>Notes</b>			
Type contains parts for a terminal located at top or bottom for 3 or 4 pole switches.			
Conversion kit for circuit-breaker with screw connection.			
Insulation using NZM4(-4)-XKSA cover or NZM4(-4)-XKP phase isolator necessary.			
When the circuit-breaker is installed on a conductive mounting plate, use of the NZM4(-4)-XKSA cover is obligatory.			
Standard with control circuit terminal for 1 x 0.75 - 2.5 mm <sup>2</sup> or 2 x 0.75 - 1.5 mm <sup>2</sup> copper conductor.			

## Design verification as per IEC/EN 61439

IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Wiring set for power circuit breaker (EC002050)
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Wiring set for circuit breaker (ecl@ss10.0.1-27-37-04-24 [ACN957011])

Suitable for number of poles			3
Model			Other

Approvals

Product Standards			CSA-C22.2 No. 5-09; IEC60947, CE marking
North America Certification			Request filed for CSA

Dimensions

--

Additional product information (links)

IL01210012Z (AWA1230-2040) Tunnel terminal, flat-conductor terminal	
IL01210012Z (AWA1230-2040) Tunnel terminal, flat-conductor terminal	<a href="https://es-assets.eaton.com/DOCUMENTATION/AWA_INSTRUCTIONS/IL01210012Z.pdf">https://es-assets.eaton.com/DOCUMENTATION/AWA_INSTRUCTIONS/IL01210012Z.pdf</a>