

# Eaton 266223

Catalog Number: 266223

Eaton Moeller series NZM - Molded Case Circuit Breaker.  
Undervoltage release, 480-525VAC, +2early N/O, 4

General specifications



Photo is representative

Product Name	Catalog Number
Eaton Moeller series NZM release	266223
EAN	Model Code
4015082662233	NZM4-XUHIV480-525AC
Product Length/Depth	Product Height
107 mm	51 mm
Product Width	Product Weight
64 mm	0.24 kg
Compliances	Certifications
IEC	CSA certified
UL/CSA	CSA (Class No. 1437-01)
RoHS conform	CSA (File No. 22086)
	UL (Category Control Number DIHS)
	UL listed
	UL489
	UL (File No. E140305)
	IEC60947
	CSA-C22.2 No. 5-09
	CE marking

## Type

Accessory Undervoltage release Undervoltage release with early-make auxiliary contact

## Special features

Undervoltage release with 2 early-make auxiliary contacts, e.g., for early-make connection of undervoltage release in main switch applications, as well as for interlock and load shedding circuits. For use with emergency-stop devices in connection with an emergency-stop button. When the under-voltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on. Early-make of auxiliary contacts on switching on (manual operation): approx. 90 ms. Undervoltage releases cannot be installed simultaneously with NZM...-XHIV... early-make auxiliary contact or NZM...-XA... shunt release. Cannot be used in conjunction with NZM...-XR... remote operator.

### 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

### 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

### 10.2.2 Corrosion resistance

Meets the product standard's requirements.

#### 10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

#### 10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

#### 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

### 10.2.4 Resistance to ultra-violet (UV) radiation

## Brochures

[eaton-feerum-the-whole-grain-solution-success-story-en-us.pdf](#)

[eaton-digital-nzm-brochure-br013003en-en-us.pdf](#)

## Catalogs

[eaton-digital-nzm-catalog-ca013003en-en-us.pdf](#)

## Certification reports

[DA-DC-03\\_NZM4](#)

## eCAD model

[DA-CE-ETN.NZM4-XUHIV480-525AC](#)

## Installation instructions

[IL01210005Z](#)

[eaton-circuit-breaker-voltage-release-nzm4-il012143zu.pdf](#)

## Installation videos

[The new digital NZM Range](#)

[Introduction of the new digital circuit breaker NZM](#)

## Technical data sheets

[eaton-nzm-technical-information-sheet](#)

Meets the product standard's requirements.

#### 10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.7 Inscriptions

Meets the product standard's requirements.

#### 10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.4 Clearances and creepage distances

Meets the product standard's requirements.

#### 10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

#### 10.8 Connections for external conductors

Is the panel builder's responsibility.

#### 10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

#### 10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

#### 10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

#### Electric connection type

Screw connection

#### Fitted with:

Two early-make auxiliary contacts

#### Frame

NZM4

#### Used with

NZM4(-4), N(S)4(-4)

Minimum command time - max

15 ms

Minimum command time - min

10 ms

Number of contacts (normally open contacts)

2

Reaction time

23 ms

Pick-up power consumption at AC (undervoltage release)

3.6 VA

Pick-up power consumption at DC (undervoltage release)

2.5 W

Voltage tolerance - max

1.1

Voltage tolerance - min

.85

Rated control supply voltage

480 - 525 V 50/60 Hz

Rated control supply voltage (Us) at AC, 50 Hz - max

525 V

Rated control supply voltage (Us) at AC, 50 Hz - min

480 V

Rated control supply voltage (Us) at AC, 60 Hz - max

525 V

Rated control supply voltage (Us) at AC, 60 Hz - min

480 V

Suitable for

Off-load switch

Connection type

With bolt connection

Voltage type

AC

Drop-out voltage of undervoltage release AC/DC - max

0.7 x Us

Drop-out voltage of undervoltage release AC/DC - min

0.35 x Us

Terminal capacity (solid/flexible conductor)

0.75 mm<sup>2</sup> - 2.5 mm<sup>2</sup> (2x) at shunt release with ferrule  
18 - 14 AWG (1x) for undervoltage releases, off-delayed  
18 - 14 AWG (1x) at shunt release  
0.75 mm<sup>2</sup> - 2.5 mm<sup>2</sup> (1x) for undervoltage releases, off-delayed  
with ferrule  
0.75 mm<sup>2</sup> - 2.5 mm<sup>2</sup> (2x) for undervoltage releases, off-delayed  
with ferrule  
18 - 14 AWG (2x) for undervoltage releases, off-delayed  
0.75 mm<sup>2</sup> - 2.5 mm<sup>2</sup> (1x) at shunt release with ferrule  
18 - 14 AWG (2x) at shunt release

#### Power consumption

3.6 VA (Sealing AC)  
2.5 W (sealing DC)

#### Rated control supply voltage (Us) at DC - max

0 V

#### Rated control supply voltage (Us) at DC - min

0 V

#### Number of contacts (normally closed contacts)

0

#### Number of contacts (change-over contacts)

0

#### Undelayed short-circuit release - min

0 A

#### Undelayed short-circuit release - max

0 A

#### Rated control voltage (relay contacts)

480 V AC  
525 V AC